

MAG4 4 Zone Fire Panel

- 4 programmable zones
- Active end of line monitoring and head removal
- 30 fire detectors per zone
- Unlimited number of call points per zone
- Integral evacuate alarm button
- 'Class change' facility
- Enable/disable security key
- One man walk test facility
- Volt free fire change over relay
- Volt free fault change over relay
- Individual sounder circuit fault ID
- Individual zone/sounder isolate
- BS5839 and EN54 P2/4 compliant
- CE certified
- Requires only 1x12v battery
- Metal casing



INPUTS	Max detectors per zone	30
	Thresholds for zone conditions	0 - 2 mA (Fault condition) 2 - 6 mA (Normal condition) 6 - 110 mA (Fire condition) 110 mA - Short (Fault condition)
POWER	Mains fail consumption	50mA
	Mains supply	230 VAC \pm 10%
	Standby supply	1 x 7ah 12V S.L.A. Battery
	Power availability	0.7 amps
OUTPUTS	Sounder 1	24V (max 300mA fused)
	Sounder 2	24V (max 300mA fused)
	Fault/fire relay	Volt free 500mA @ 24V (max load)
	Auxiliary output	24VDC (300mA fused)
ENVIRONMENT	Working Temperature	0 to 40 OC
	Storage Temperature	-20 to 60 OC
	Humidity	0 - 95%
	Dimensions (mm)	320W 220H 80D
	Weight	3.5 KG