

**Product Code:** CL1835B

**Description:** 13A 1 Gang Double Pole Safety Shutter Switched Socket Outlet With Neon



### General Information

<b>Dimensions</b>	80mm (W) x 80mm (H) x 42mm (D)
<b>Finish</b>	Metal Clad Grey
<b>Materials</b>	Front Plate & Pattress Box: Electrophoretically Coated Steel Insert & Rocker Switch: Urea Rear Housing: Urea Terminals: Brass Terminal Screws: Steel & Yellow Passivated Contacts: Silver "on-lay" Copper / Brass Internal Busbars: Formed Pressed Brass Earth Strap: Mild Steel
<b>Maximum Voltage</b>	250V~ 50Hz
<b>Load Rating</b>	13A
<b>Plate Fixing Centres</b>	60.3mm
<b>Terminal Size</b>	5mmø
<b>Terminal Torque</b>	2.5Nm
<b>Terminal Capacity</b>	4 x 2.5mm <sup>2</sup> , 2 x 4mm <sup>2</sup>
<b>Double Pole</b>	Yes
<b>Neon Indicator</b>	Yes (Red)
<b>Back Box Depth</b>	40mm Supplied
<b>Earth Terminal Provided</b>	Yes
<b>Back Box Knockouts</b>	None
<b>Operational Temperature</b>	-5°C to +40°C
<b>Warranty</b>	10 Years

**Standards** BS 1363-2: 2016 +A1: 2018

### Additional Information

Ensure that the mains supply is isolated before commencing installation and refer to the circuit diagram with the relevant product.  
Bare earth cables must always be covered with appropriate sleeving and wired to the earth terminal. The safety shutter will only fully open when all three BS 1363 plug-top pins engage correctly with the shutter. Inserting the earth pin alone will not open the live and neutral shutter like conventional socket shutters.